

Installation instruction build on “EVION”

General instruction

Read this instruction with care. After installation save the instruction for future reference and maintenance.

Safety

- Before installation, maintenance or changing of the lamp, the electricity to the source of light has to be switched off.
- For installation of the luminaire a qualified electric engineer is recommended. The luminaire must be installed in compliance with the most recent stipulations and installation instructions.
- Check the total capacity of the actual current circuit, this may not exceed the maximum allowed capacity of the section.
- All replacement parts must be equal to the original parts.
- Do not cover luminaires with isolation or similar materials.

Product specification

- This first class luminaire has to be earthed.
- IP20 classified, unless mentioned otherwise.
- To be used on surfaces with normal risk of fire.
- It is recommended that the surrounding temperature is less than 25°C.
- 230/240V AC 50Hz.
- CE marked.
- This product is designed and produced in compliance with stipulations of: EN55015; EN 60592-2; EN 60598-2-2.

Installation

- Remove the opal front diffuser from the base of the luminaire. To do so, push it in, grab the edge and pull it out. **Note:** Preferably use gloves to avoid damaging the hood.
- This luminaire has a mounting plate for installation of parts.
- Select a suitable cable entry point, located on the mounting plate.
- Position and fix the housing on a suitable flat and solid surface.
- Connect the power cable to the connector on the mounting plate. Make sure correct polarity is observed and the luminaire is earthed. Also make sure that the connection takes place according to applicable standards.
- Fit the lamp into the lamp holder. We recommend you to use an A-type brand lamp.
- Refit the opal diffuser by pushing it in.
- Restore power supply, switch on and test for correct operation.

Lamp type

Inside is a label which type lamp you should use, if applicable.

Do NOT diverge!

To guarantee the dependability and correct operation, the installation instructions must be followed up correctly. Changes are not allowed. When changes are made on the luminaires, the warranty will expire. Emilux B.V. does not take any responsibility when luminaires are modified in any way!

